

WINCO®

Quality Generators Since 1927

HPS6000HE

EPA
 APPROVED

Engine:

- Honda GX340 OHV
- EPA certified design for use with gasoline or natural gas
- Commercial grade engine with cast iron cylinder sleeves
- 3 year warranty
- Special carburetor and secondary gas regulator allows the engine to operate on the most convenient fuel - gasoline or natural gas
- Maintenance-free electronic ignition system
- Low oil protection helps prevent costly repairs and downtime

Generator End:

- 100% copper windings - longer life and improved motor starting
- Dampers, skewed rotors for <6% harmonic distortion
- Capacitor excitation for brushless operation

Components:

- 7 gallon steel fuel tank with fuel gauge
- Heavy duty 1"-14 gauge tubular steel cradle
- Industrial powder coat paint
- Electric/Recoil start (NG operation requires electric start)
- Full receptacle package with circuit breaker protection
- 120/240 volt receptacle for connection to a temporary power distribution system or to a building electrical service with an approved manual transfer switch for emergency/standby use
- Vibration isolation for smooth operation
- Easy to move, convenient to store

Accessories (optional):

- Two-wheel dolly kit
- Generator cover
- Low pressure fuel solenoid kit
- WINCO manual transfer switch
- Plug-in line voltage monitor
- 30 amp (NEMA L14-30P) plug

BI-FUEL  **NATURAL GAS**
GASOLINE

HOME POWER®

SURGE WATTS ⁽¹⁾	6000
CONTINUOUS WATTS ⁽¹⁾	5500
AMPS ⁽¹⁾	45.8/22.9
VOLTS	120/240
VOLTAGE REGULATION	+/- 5%
FREQUENCY REGULATION	+/- 3%
ENGINE BRAND	HONDA
ENGINE MODEL	GX340
ENGINE STARTER ⁽³⁾	ELECTRIC/RECOIL
ENGINE SPEED	3600 RPM
DISPLACEMENT	389 CC
ENGINE CYLINDERS	SINGLE
LOW OIL PROTECTION	STANDARD
dBAAT 7 METERS	72
FUEL TANK	7 GAL
FUEL USE: GASOLINE	1.0 gal/hr
NATURAL GAS	160 ft ³ /hr - 163,200 BTU/hr
MOTOR STARTING (CODE G) ^{(1) (2)}	2 HP
MAIN CIRCUIT BREAKER	25A
120 VOLT RECEPTACLES	2 x NEMA 5-20R 20A
120/240 VOLT RECEPTACLES	1 x NEMA L14-30R 30A
DIMENSIONS (LxWxH)	32.75" x 22.5" x 22"
NET WEIGHT	202 lbs
SHIP WEIGHT	224 lbs
WARRANTY (ENG/GEN) ⁽⁴⁾	3 YRS / 2 YRS

NOTES: (1) Based on gasoline fuel. Derate 20% for Natural Gas. (2) Code G capacitor start motor. (3) Electric start models include battery rack and cables, battery not included. BCI Group 20 or 24HL, 12-volt, 300 CCA battery required. (4) Prime Power Warranty 120 days. Contact your local Honda engine service center for engine warranty assistance.

Presented by:


Millenium
 Products Inc.
 6346 Heron Parkway
 Clarkston, MI 48346
www.milleniumproducts.net
info@milleniumproducts.net