2000 Watt Inverter Generator

WI2000P

The super quiet WI2000P gives you plenty of clean, pure power in a compact, portable design. Advanced inverter technology provides reliable power to a computer, radio or television, as well as other sensitive equipment, yet it is powerful enough to run a small refrigerator. With its parallel capability, you can connect an additional parallel generator to increase power output. A powerful 500-watt mobile floodlight attachment is optional. This model is EPA and CARB compliant.

Features

- Plenty of power for small appliances
- 2000 watts maximum load
- Parallel ready
- Smart throttle
- 3½-hour continuous runtime

Accessories

Included

- Oil fill bottle
- Spare spark plug
- Spark plug wrench and handle

Optional

- 500-watt LED floodlight
- 30-amp parallel kit
- 50-amp parallel kit

Specifications

AC voltage	120 V	Engine type	Air-cooled, single-cylinder, four-stroke, vertical-shaft OHV
Frequency	60 Hz		
Max. output	2000 W	Output power	2.95 hp @ 4500 rpm
Rated output	1600 W	Displacement	106 cc
Max. current	16.6 A	Noise level @ 23 ft. (7m)	57 dB @ no load
Rated current	13.3 A		61 dB @ full load
DC output	12 V @ 5.0 A	Continuous run time	3.5 hrs. @ rated load
Ignition system	TCI	Fuel capacity	1 gal. (3.8L)
Starting system	Recoil	Fuel type	Automotive unleaded gasoline
Phase	Single	Standards compliance	EPA, CARB
Electronic circuit breaker	Inverter controlled	Dimensions, L × W × H	20.3 × 11.8 × 16.9 in. (52 × 30 × 43cm)
Engine model	KG158	Dry weight	49 lbs. (22kg)
		Receptacles	One 120Vac 20A GFCI duplex

DERATINGS:
RATINGS APPLY FOR ALTITUDES FROM SEA LEVEL UP TO 1,000 FEET (304.8 METERS) WITH TYPICAL COOLING, NORMAL AMBIENTS AND GASOLINE FUEL. REDUCE RATINGS 3.5% FOR EACH 1000 FEET (305 METERS) ABOVE SEA LEVEL AND 1.0% FOR EACH 10 °F RISE ABOVE 60 °F (5.556 °C ABOVE 20 °C):

ALL INFORMATION SUBJECT TO CHANGE WITHOUT NOTICE. Rev 2017-10-09